

NAG Library Routine Document

F06HRF

Note: before using this routine, please read the Users' Note for your implementation to check the interpretation of ***bold italicised*** terms and other implementation-dependent details.

1 Purpose

F06HRF generates a complex elementary reflection.

2 Specification

```
SUBROUTINE F06HRF (N, ALPHA, X, INCX, TOL, THETA)
  INTEGER          N, INCX
  REAL (KIND=nag_wp) TOL
  COMPLEX (KIND=nag_wp) ALPHA, X(*), THETA
```

3 Description

F06HRF generates details of a complex elementary reflection (Householder matrix), P , such that

$$P \begin{pmatrix} \alpha \\ x \end{pmatrix} = \begin{pmatrix} \beta \\ 0 \end{pmatrix}$$

where P is unitary, α is a complex scalar, β is a real scalar, and x is an n -element complex vector.

P is given in the form

$$P = I - \gamma \begin{pmatrix} \zeta \\ z \end{pmatrix} (\zeta \quad z^H),$$

where z is an n -element complex vector, γ is a complex scalar such that $\text{Re}(\gamma) = 1$, and ζ is a real scalar. γ and ζ are returned in a single complex value $\theta = (\zeta, \text{Im}(\gamma))$. Thus $\zeta = \text{Re}(\theta)$ and $\gamma = (1, \text{Im}(\theta))$.

If x is such that

$$\max(|\text{Re}(x_i)|, |\text{Im}(x_i)|) \leq \max(\text{tol}, \epsilon \max(|\text{Re}(\alpha)|, |\text{Im}(\alpha)|)),$$

where ϵ is the ***machine precision*** and tol is a user-supplied tolerance, then:

either θ is set to 0, in which case P can be taken to be the unit matrix;

or θ is set so that $\text{Re}(\theta) \leq 0$ and $\theta \neq 0$, in which case

$$P = \begin{pmatrix} \theta & 0 \\ 0 & I \end{pmatrix}.$$

Otherwise $1 \leq \text{Re}(\theta) \leq \sqrt{2}$.

4 References

None.

5 Arguments

1: N – INTEGER

Input

On entry: n , the number of elements in x and z .

- 2: ALPHA – COMPLEX (KIND=nag_wp) Input/Output
On entry: the scalar α .
On exit: the scalar β .
- 3: X(*) – COMPLEX (KIND=nag_wp) array Input/Output
Note: the dimension of the array X must be at least $\max(1, 1 + (N - 1) \times \text{INCX})$.
On entry: the n -element vector x . x_i must be stored in $X(1 + (i - 1) \times \text{INCX})$, for $i = 1, 2, \dots, N$.
Intermediate elements of X are not referenced.
On exit: the referenced elements are overwritten by details of the complex elementary reflection.
- 4: INCX – INTEGER Input
On entry: the increment in the subscripts of X between successive elements of x .
Constraint: $\text{INCX} > 0$.
- 5: TOL – REAL (KIND=nag_wp) Input
On entry: the value tol .
- 6: THETA – COMPLEX (KIND=nag_wp) Output
On exit: the scalar θ .

6 Error Indicators and Warnings

None.

7 Accuracy

Not applicable.

8 Parallelism and Performance

F06HRF makes calls to BLAS and/or LAPACK routines, which may be threaded within the vendor library used by this implementation. Consult the documentation for the vendor library for further information.

Please consult the X06 Chapter Introduction for information on how to control and interrogate the OpenMP environment used within this routine. Please also consult the Users' Note for your implementation for any additional implementation-specific information.

9 Further Comments

None.

10 Example

None.
